

QAC1100

Atlas Copco QAC1100 Silenced
Generator: TwinPower



General Information (50Hz | 60Hz)

Rated Frequency	Hz	50 60	Sound Power Level (LwA)	dB (A)	105
Rated Voltage	V	400	Min/Max Ambient	°C	-25/50
Prime Rated Power	kVA/kW	1000/800	Fuel Consumption @ 75% Load to 100% Load (l/hr)	l/hr	152 to 203 156 to 208
Rated Current	A	1400	Fuel Tank Capacity	l	1640

Dimensions

Containerised

Size (L x W x H)	mm	6060 x 2500 x 2600
Mass - Dry	kg	10400
Mass - Wet	kg	11965

Optional Accessories

Cables – 20m (Recommended 4 sets of 185mm 4 core + 1 x 95mm Earth Cable)	Transformers
Distribution Boards	External Fuel Tanks

Other Features

9 Kg Fire Extinguisher	Strobe Light (Indicating units is operational)
Buzz Bar	Specialized Eye Lifting Hooks
External Fuel Tank Connection	Emergency Stop Switch
Parallelling with Compatible Generators	Remote and Auto Start
4-Pole Battery Isolator Switch	Spillage Free Frame
Automatic Mains Failure (AMF)	



AIR



POWER



TEMPERATURE



FLOW

www.randair.com

Rand-Air South Africa (Pty) Ltd.

Subject to change without prior notice. Information is for guidance only.
Please contact your nearest Rental office for detailed application advice.