

QAC1450

Atlas Copco QAC1450 Silenced
Generator: TwinPower



General Information (50Hz | 60Hz)

Rated Frequency	Hz	50 60	Sound Power Level (LwA)	dB (A)	105
Rated Voltage	V	400	Min/Max Ambient	°C	-25/50
Prime Rated Power	kVA/kW	1447/1158	Fuel Consumption @ 75% Load to 100% Load (l/hr)	l/hr	207 to 276 216 to 288
Rated Current	A	2200	Fuel Tank Capacity	l	1640

Dimensions

Containerised

Size (L x W x H)	mm	6060 x 2500 x 2600
Mass - Dry	kg	14900
Mass - Wet	kg	16500

Optional Accessories

Cables – 20m (Recommended 4 sets of 185mm 4 core + 1 x 95mm Earth Cable)	Transformers
Distribution Boards	External Fuel Tanks

Other Features

9 Kg Fire Extinguisher	Strobe Light (Indicating units is operational)
Buzz Bar	Specialized Eye Lifting Hooks
External Fuel Tank Connection	Emergency Stop Switch
Parallelling with Compatible Generators	Remote and Auto Start (Only for certain models)
4-Pole Battery Isolator Switch	Spillage Free Frame
Automatic Mains Failure (AMF) (Only for certain models)	



AIR



POWER



TEMPERATURE



FLOW

www.randair.com

Rand-Air South Africa (Pty) Ltd.

Subject to change without prior notice. Information is for guidance only.
Please contact your nearest Rental office for detailed application advice.